



GE  
Lighting

97596 - GE Ecolux® Blax® T4 - Facilities; Retail Display; Hospitality;  
Office; Restaurant; Warehouse

F13DBX/835/ECO4P

### Product Photo



### GENERAL CHARACTERISTICS

|                                 |  |
|---------------------------------|--|
| Base Type                       | Pin/Plug-In  |
| Mercury Content                 | 3 mg   |
| Rated Life Hours-nominal        | 17000 h  |
| Starting Temp (MIN) C-degrees   | 0 °C   |
| Mercury-Picogram per mean lm hr | 198.7  |
| Primary Application             | Facilities<br>Retail Display<br>Hospitality<br>Office<br>Restaurant<br>Warehouse |
| Product Technology              | Compact Fluorescent  |
| Base                            | G24q-1   |
| Bulb Shape                      | A19  |

### PHOTOMETRIC CHARACTERISTICS

|                                |        |
|--------------------------------|--------|
| Mean Lumens nominal            | 755 lm |
| Nominal Initial Lumen per Watt | 69     |
| Initial Lumens-nominal         | 900 lm |
| Color Rendering Index-CRI      | 82     |
| Color Temperature              | 3500 K |

### PRODUCT INFORMATION

|                             |                  |
|-----------------------------|------------------|
| Product Code                | 97596            |
| Description                 | F13DBX/835/ECO4P |
| Alternative Unit Of Measure | PACK             |

### DIMENSIONS

|                             |        |
|-----------------------------|--------|
| Base Face to Top of Lamp    | 4.4 in |
| Nominal Length              | 5.0 in |
| Bulb Max Overall Length-MOL | 4.9 in |

### ELECTRICAL CHARACTERISTICS

|                                |       |
|--------------------------------|-------|
| Equivalent Incandescent Watts  | 60 W  |
| Current Crest Factor (MAX)     | 5.25  |
| Supply Current Freq nominal Hz | 60 Hz |
| Rated power (Watts)            | 13 W  |

### CAUTIONS & WARNINGS

#### Caution

Lamp may shatter and cause injury if broken

Remove and install by grasping only plastic portion of the lamp.

### NOTES

4-Pin lamp minimum starting temperature is a function of the ballast. Most ballasts are rated with a minimum starting temperature of 50 degrees F (10 C). Ballasts are also available that provide reliable starting to 0 degrees F (-18C) and -20 F (-29C).

